

# DRIVING CIRCUIT FOR ORGANIC ELECTROLUMINESCENCE DEVICE

## BACKGROUND OF THE INVENTION

### Field of the Invention

[01] The present invention relates to a driving circuit of a display device, and more particularly, to a driving circuit of an organic electroluminescence (EL) device using a DC-DC converter.

### Background of the Related Art

[02] Recently, a flat display market is rapidly developing.

[03] A flat display, developed beginning with liquid crystal displays (LCD), has received much attention. A cathode ray tube (CRT), which had been generally used in the field of display for several decades, is recently being replaced with flat displays such as Plasma Display Panel (PDP), Visual Fluorescent Display (VFD), Field Emission Display (FED), Light Emitting Diode (LED), and Electro-luminescence (EL).

[04] With development of the flat display, many studies for decreasing a size of Integrated Circuits (IC) used in the flat display and decreasing the number of external parts are in progress.

[05] A power supply is separately formed outside the ICs without being formed inside the ICs for some reasons. Since ICs

for power supply, sold in the market, are separately used, several limitations according to miniaturization and low cost occur.

[06] FIG. 1 is a block diagram illustrating a structure of a related art driving circuit for an organic EL device.

[07] As shown in FIG. 1, the related art driving circuit is divided into an internal circuit portion and an external circuit portion.

[08] Referring to FIG. 1, the external circuit portion includes a power supply 10, a power peripheral unit 20, and an external micro control unit (MCU) 90. The power supply 10 supplies the required power to all parts of the organic EL device. The power peripheral unit 20 consists of an inductor, a diode, and a resistor.

[09] Meanwhile, the internal circuit portion includes an interface unit 50 interfacing display information from the MCU 90, a memory 60 storing the display information transmitted through the interface unit 50, a data processor 30 outputting a display data to a display panel 80 using the display information stored in the memory 60 and a direct current (DC) voltage provided from the power supply 10, a scan processor 40 outputting a scan data to the display panel 80, and a timing control unit 70 controlling a whole timing required for the display.

[10] The related art control unit includes most components inside an IC, however, a power portion, i.e., the power supply 10 and the power peripheral unit 20 are provided outside the IC.

[11] As has been explained, the related art driving circuit for an organic EL device should control the DC voltage supplied to the display panel considering several factors such as external voltage fluctuation.

[12] At this time, additional devices or parts are required outside the IC to properly control the DC voltage.

[13] Also, since the power portion is provided outside the IC, hardware required to connect internal components of the IC with the external power portion is additionally required. For this reason, a volume of the organic EL display device increases, thereby causing difficulty in using the driving circuit.

#### SUMMARY OF THE INVENTION

[14] Accordingly, the present invention is directed to a driving circuit for an organic EL display device that substantially obviates one or more problems due to limitations and disadvantages of the related art.

[15] An object of the present invention is to provide a driving circuit for an organic EL display device that can control a DC voltage inside an IC.

[16] Another object of the present invention is to provide a one-chip driving circuit for an organic EL display device having a power supply inside an IC.

[17] Other object of the present invention is to provide a driving circuit for an organic EL display device that can reduce the size and the cost.

[18] Additional advantages, objects, and features of the invention will be set forth in part in the description which follows and in part will become apparent to those having ordinary skill in the art upon examination of the following or may be learned from practice of the invention. The objectives and other advantages of the invention may be realized and attained by the structure particularly pointed out in the written description and claims hereof as well as the appended drawings.

[19] To achieve these objects and other advantages and in accordance with the purpose of the invention, a driving circuit for an organic EL display device includes a DC-DC converter provided inside one chip, for converting an external DC voltage to a desired DC voltage, the DC-DC converter being controlled by a timing control signal for controlling timing of the organic EL display device.

[20] In one aspect of the present invention, a driving circuit for an organic EL display device includes a DC-DC converter provided inside one chip, for controlling an external

1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425	2426	2427	2428	2429	2430	2431	2432	2433	2434	2435	2436	2437	2438	2439	2440	2441	2442	2443	2444	2445	2446	2447
------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------

1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425	2426	2427	2428	2429	2430	2431	2432	2433	2434	2435	2436	2437	2438	2439	2440	2441	2442	2443	2444	2445	2446	2447
------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------

[22] Preferably, the DC-DC converter includes a mode control unit outputting a voltage control signal in response to the timing control signal from the timing control unit, an

impedance generating unit outputting an impedance value changed depending on the voltage control signal output from the mode control unit, a resistor connected with an output terminal of the DC-DC converter in parallel and with an output terminal of the impedance generating unit in series, and a voltage control unit receiving a feedback value of the controlled DC voltage distributed by the impedance value output from the impedance generating unit and a value of the resistor, and then outputting a DC voltage controlled according to the feedback voltage.

[23] It is to be understood that both the foregoing general description and the following detailed description of the present invention are exemplary and explanatory and are intended to provide further explanation of the invention as claimed.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[24] The accompanying drawings, which are included to provide a further understanding of the invention and are incorporated in and constitute a part of this application, illustrate embodiment(s) of the invention and together with the description serve to explain the principle of the invention. In the drawings:

[25] FIG. 1 is a diagram illustrating a structure of a related art driving circuit for an organic EL device;

[26] FIG. 2 is a diagram illustrating a structure of a driving circuit for an organic EL device in accordance with the present invention; and

[27] FIG. 3 is a diagram illustrating a structure of a power portion in accordance with the present invention.

#### DETAILED DESCRIPTION OF THE INVENTION

[28] Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings.

[29] FIG. 2 is a block diagram illustrating a structure of a driving circuit for an organic EL device in accordance with the present invention.

[30] Referring to FIG. 2, the driving circuit includes a data processor 30, a scan processor 40, an interface unit 50, a memory 60, a timing control unit 70, and a DC-DC converter 110.

[31] The DC-DC converter 110 is provided inside the driving circuit which is an IC.

[32] Also, the DC-DC converter 110 controls a DC voltage externally provided by timing control signals and provides the controlled DC voltage to the other components inside the driving circuit.

[33] The interface unit 50 interfaces the components of the driving circuit with an external MCU located outside the driving circuit.

[34] The memory 60 stores display information transmitted through the interface unit 50.

[35] The data processor 30 outputs a display data for a display panel 80 using the display information stored in the memory 60 and a predetermined DC voltage output from the DC-DC converter 110.

[36] The scan processor 40 outputs scan signals to the display panel 80 according to the display information from the memory 60.

[37] The timing control signals output from the timing control unit 70 are provided to all components of the one-chip driving circuit. That is, the timing control signals are used as control signals required to provide the display data and the scan data to the display panel 80 and to allow the DC-DC converter 110 to convert the external DC voltage to a desired DC voltage.

[38] Meanwhile, in FIG. 2, the power peripheral unit 120 controls input and output voltages of the DC-Dc converter 110 within the one-chip driving circuit.

[39] Also, the power peripheral unit 120 stabilizes the operation of the DC-DC converter 110, which is to prevent

backward current from occurring and to maintain the input voltage for a predetermined time.

[40] The power peripheral unit 120 includes an inductor, a diode, and a resistor, which cannot be installed inside the IC, so that those are installed outside the IC.

[41] A structure of the DC-DC converter 110 and the power peripheral unit 120 will be described in detail with reference to FIG. 3.

[42] FIG. 3 is a detailed block diagram illustrating a circuit of the DC-DC converter 110 and the power peripheral unit 120.

[43] Referring to FIG. 3, the DC-DC converter 110 includes a mode control unit 111, an impedance generating unit 112, a voltage control unit 113, and a resistor R1.

[44] The mode control unit 111 generates a voltage control signal for controlling a constant DC voltage supplied from the power peripheral unit 120 in response to the timing control signals output from the timing control unit 70.

[45] The impedance generating unit 112 outputs an impedance value properly changed depending on the voltage control signal output from the mode control unit 111.

[46] The voltage control unit 113 inputs an output voltage  $V_o$ , distributed in an appropriate proportion according to the changed impedance output from the impedance generating unit 112

and the resistor R1 connected with the impedance generating unit 112 in series, through a feedback terminal FB. The voltage control unit 113 outputs the controlled DC voltage  $V_o$  using the input voltage  $V_i$  and the feedback voltage.

[47] Meanwhile, in FIG. 3, the impedance generating unit 112 and the resistor R1 may be installed both inside and outside the IC. As shown in FIG. 3, the power peripheral unit 120 for changing the voltage, which is installed outside the IC, is connected with its input terminal  $V_{in}$  and its output terminal  $V_{out}$  in parallel, and includes a first stabilized capacitor C1 and a second stabilization capacitor C2 to minimize fluctuation of the input voltage  $V_i$  and the output voltage  $V_o$ . It is preferable that the capacitors C1 and C2 have a large capacity as much as possible.

[48] The power peripheral unit 120 includes an inductor L and a diode D. The inductor is connected in series between the input terminal  $V_{in}$  and the output terminal  $V_{out}$  to maintain the input voltage  $V_i$  applied to the voltage control unit 113 for a predetermined time to adjust a desired voltage. The diode is connected between the voltage control unit 113 and the output terminal  $V_{out}$ , and prevents a backward current from occurring in the power peripheral unit 120.

[49] As has been explained, the operation of the driving circuit for an organic EL device will be described in detail with reference to FIG. 2 and FIG. 3.

[50] First, the timing control unit 70 provides the timing control signal to the DC-DC converter 110. Then, the mode control unit 112 generates the voltage control signal for converting the external DC voltage from the power peripheral unit 120 to a desired DC voltage value in response to the timing control signal.

[51] That is, the mode control unit 112 generates a voltage control signal corresponding to the timing control signal.

[52] Subsequently, the voltage control signal is transmitted to the impedance generating unit 112. The impedance generating unit transmits an impedance value corresponding to the input voltage control signal to the feedback terminal FB of the voltage control unit 113.

[53] Meanwhile, the voltage control unit 113 internally controls an external DC voltage, which is applied through the input terminal Vin of the power peripheral unit 120, using the impedance input through the feedback terminal FB. Then, the voltage control unit 113 outputs the controlled DC voltage through its output terminal SW. The output DC voltage is output as an output signal of the DC-DC converter 110 through the output terminal Vout in the power peripheral unit 120.

[54] Subsequently, the output signal of the DC-DC converter 110, output through the output terminal Vout, is input to the data processor 30 and the scan processor 40.

[55] Meanwhile, the display information is transmitted from the MCU 90 to the memory 60 through the interface unit 50 and then stored in the memory 60. The display information is input to the data processor 30 and the scan processor 40, together with the controlled DC voltage output from the DC-DC converter 110.

[56] Subsequently, the data processor 30 and the scan processor 40 respectively generate the display data and the scan data based on the display information and the controlled DC voltage output from the DC-DC converter 110 in response to the timing control signal provided from the timing control unit 70. The data processor 30 and the scan processor 40 output the display data and the scan data to the display panel 80.

[57] Accordingly, a character and a video corresponding to the display data and the scan data are displayed on the display panel 80, which have a brightness corresponding to the controlled DC voltage output from the DC-DC converter 110.

[58] As has been explained, the driving circuit for an organic EL device according to the present invention has the following advantages.

[59] First, since the DC-DC converter and the power peripheral unit are installed inside the IC of the driving

circuit, parts installed outside the driving circuit decrease. Therefore, the manufacturing cost of the EL display device can be reduced and its volume can be minimized.

[60] Furthermore, voltage control signals for various modes can be generated inside the IC of the driving circuit according to the timing control signal. Accordingly, it is possible to obtain the desired DC voltage value with convenience and exactness.

[61] The forgoing embodiments are merely exemplary and are not to be construed as limiting the present invention. The present teachings can be readily applied to other types of apparatuses. The description of the present invention is intended to be illustrative, and not to limit the scope of the claims. Many alternatives, modifications, and variations will be apparent to those skilled in the art.